



CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited
PRIMEPOWER650 (1350MHz)

SPECint2000 = 905
SPECint_base2000 = 776

SPEC license #: 19 Tested by: Fujitsu Limited Test date: Jun-2003 Hardware Avail: Aug-2003 Software Avail: May-2003

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio	500 1000 1500 2000			
164.gzip	1400	220	636	198	706	[Bar chart showing ratio]			
175.vpr	1400	204	685	189	741	[Bar chart showing ratio]			
176.gcc	1100	155	711	119	922	[Bar chart showing ratio]			
181.mcf	1800	268	673	177	1017	[Bar chart showing ratio]			
186.crafty	1000	117	856	113	885	[Bar chart showing ratio]			
197.parser	1800	265	680	242	744	[Bar chart showing ratio]			
252.eon	1300	220	592	146	888	[Bar chart showing ratio]			
253.perlbnk	1800	204	883	202	890	[Bar chart showing ratio]			
254.gap	1100	156	707	145	756	[Bar chart showing ratio]			
255.vortex	1900	141	1350	107	1781	[Bar chart showing ratio]			
256.bzip2	1500	189	792	179	836	[Bar chart showing ratio]			
300.twolf	3000	301	996	286	1047	[Bar chart showing ratio]			

Hardware

CPU: SPARC64 V
CPU MHz: 1350
FPU: Integrated
CPU(s) enabled: 1 core, 1 chip, 1 core/chip
CPU(s) orderable: 1 to 8 (increments of 1)
Parallel: None
Primary Cache: 128KBI+128KBD on chip
Secondary Cache: 2MB(I+D) on chip
L3 Cache: None
Other Cache: None
Memory: 8192MB
Disk Subsystem: 1 x 36.4GB SCSI (10000rpm)
Other Hardware: None

Software

Operating System: Solaris8 2/02 with current patches (see notes)
Compiler: Fujitsu Parallelnavi 1.0.2
Sun ONE Studio 8
Sun Performance Library 8
File System: ufs
System State: multi user

Notes/Tuning Information

Baseline (except 252.eon, for Sun ONE Studio 8):

```
-fast -xtarget=ultra3cu -xipo=2 ONESTEP=yes
fdo_pre0=rm -rf ./feedback.profile ./SunWS_cache
PASS1=-xprofile=collect:./feedback
PASS2=-xprofile=use:./feedback
```

Baseline (252.eon, for Sun ONE Studio 8):

```
-fast -xchip=ultra3cu -xarch=v8plusb -xipo=2 ONESTEP=yes
```

Peak

(for Sun ONE Studio 8)

```
fdo_pre0=rm -rf ./feedback.profile ./SunWS_cache
PASS1=-xprofile=collect:./feedback
PASS2=-xprofile=use:./feedback
```

```
164.gzip: -x05 -xchip=ultra2 -xcache=128/64/2:2048/64/4 -xarch=v8plusb
-xalias_level=std -xipo=2 -xprefetch
-W2,-whole,-Ainline ONESTEP=yes
```

```
175.vpr: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
-xchip=ultra2 -xalias_level=std -xipo=2 -xsfpcnst -xdepend -W2,-whole
-Wc,-Qeps:enabled=1,-Qeps:do_spec_load=1,-Qeps:rp_filtering_margin=100
-lmopt -lm ONESTEP=yes
```



CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited
PRIMEPOWER650 (1350MHz)

SPECint2000 = 905
SPECint_base2000 = 776

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Jun-2003 | Hardware Avail: Aug-2003 | Software Avail: May-2003

Notes/Tuning Information (Continued)

```

176.gcc: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xprefetch=latx:2.0 -W2,whole
        -Wc,-Qgsched-trace_late=1,-Qgsched-T4 -l12amm ONESTEP=yes
181.mcf: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra2 -xipo=2 -xdepend -Wc,-Qms_pipe-pref,-Qeps:enabled=1
        -xprefetch_level=3 -W2,-Apf:l1list=3:notinl1list -lprism32 ONESTEP=yes
186.crafty: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xipo=2 -xalias_level=strong
        -W2,-Ashort_ldst ONESTEP=yes
197.parser: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xipo=2 -xalias_level=strong -xdepend -xregs=syst
        -Wc,-Qgsched-trace_late=1,-Qgsched-T6,-Qipa:valueprediction -lprism32 ONESTEP=yes
252.eon: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xregs=syst -xalias_level=compatible -noex -xunroll=3
        -xprefetch=latx:0.8 -Qoption iropt -Mt2000
        -Qoption cg -Qgsched-trace_late=1,-Qgsched-T4,-Qeps:enabled=1,-Qeps:ws=32
        -lmopt ONESTEP=yes
253.perlbnk: -dn -x05 -xchip=ultra3 -xcache=128/64/2:2048/64/4
        -xarch=v8plus -xipo=2 ONESTEP=yes
254.gap: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xalias_level=strong -xvector -xprefetch_level=3
        -W2,-whole,-Abcopy -Wc,-Qgsched-trace_late=1,-Qgsched-T4 ONESTEP=yes
255.vortex: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra2 -xrestrict -xipo=2 -xdepend -xprefetch=latx:2.4
        -W2,-crit,-Ainline:recursion=1:cs=500:irs=6000,-Aheap,-reroll=1,-Aunroll,-Ms15,-Mt300,-Mr6000
        -Wc,-Qeps:enabled=1,-Qeps:do_spec_load=1,-Qdepgraph-early_cross_call=1
        -Wc,-Qiselect-funcalign=32,-Qpeep-Sh0 -l12amm -lprism32 ONESTEP=yes
256.bzip2: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo -xalias_level=strong -xdepend -xregs=syst
        -xrestrict -xprefetch=latx:1.6 -W2,-Abopt
        -Wc,-Qiselect-funcalign=64,-Qeps:enabled ONESTEP=yes

```

(for Parallelnavi 1.0.2)

```

300.twolf: -Kfast_GP=5,GREG,popt,cfunc,staticclump,use_rodatta,
        xi=10,nounroll,largepage,bcopy,prefetch=4 -dy
        PASS1=-Kpg PASS2=-Kpu=$(EXEBASE).fbk
        ONESTEP=yes

```

Portability:

```

176.gcc: -Dalloca=__builtin_alloca -DHOST_WORDS_BIG_ENDIAN
186.crafty: -DSUN
252.eon: -library=iostream
253.perlbnk: -DSPEC_CPU2000_SOLARIS
254.gap: -DSYS_IS_USG -DSYS_HAS_TIME_PROTO -DSYS_HAS_SIGNAL_PROTO
        -DSYS_HAS_CALLOC_PROTO -DSYS_HAS_IOCTL_PROTO

```

Note:

```

System Tunables: (for /etc/system)
set consistent_coloring=1,
set shmsys:shminfo_shmmax=4294967296,set shmsys:shminfo_shmmni=256,
set shmsys:shminfo_shmseg=400,set shmsys:shminfo_shmmmin=1
set tune_t_fsflushr = 86400
set autoup = 86400

```

```

System Tunables: (for /etc/opt/FJSVpnm/lpg.conf)
TSS=1024M, SHMSEGSIZE=256M

```

Shell Environments:



CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited
PRIMEPOWER650 (1350MHz)

SPECint2000 =	905
SPECint_base2000 =	776

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Jun-2003 | Hardware Avail: Aug-2003 | Software Avail: May-2003

Notes/Tuning Information (Continued)

```
LD_LIBRARY_PATH="/opt3/SUNWspro/prod/lib/v8plusb"  
PRISM_HEAP=268435456  
PRISM_MODE=2
```

ONESTEP=yes was set for all baseline and peak benchmarks.
Feedback directed optimization was used for all baseline and peak benchmarks except 252.eon(base).
Small configuration memory system mode used ("4cpu mode", enabled via front panel).
Stack size set to unlimited via "ulimit -s unlimited".
System board used with only one CPU present.
Sun ONE Studio 8, posted at URL <http://www.sun.com/software/sundev/suncc/> was used for this submission.
All patches for Solaris8 posted at http://access1.sun.com/patch.public/cgi-bin/show_list.cgi/wrk/Sun_ONE_Studio_7_SPARC_SunOS_5.8 as of date 2003/04/21 were applied: 108434-12, 108435-12, 111697-04, 111721-03.