



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Supermicro

PDSLA/E Motherboard(Intel Pentium D 3.2GHz)

SPECint_rate2000 = 31.2

SPECint_rate_base2000 = 31.0

SPEC license #01176 | Tested by: Supermicro | Test date: Jun-2005 | Hardware Avail: May-2005 | Software Avail: Aug-2004

Benchmark	Base Copies	Base Runtime	Base Ratio	Copies	Runtime	Ratio
164.gzip	2	131	24.7	2	132	24.6
175.vpr	2	165	19.7	2	160	20.2
176.gcc	2	65.6	38.9	2	65.6	38.9
181.mcf	2	192	21.7	2	192	21.7
186.crafty	2	85.2	27.2	2	85.5	27.1
197.parser	2	150	27.9	2	148	28.1
252.eon	2	71.0	42.5	2	68.7	43.9
253.perlbnk	2	109	38.3	2	109	38.3
254.gap	2	68.5	37.2	2	68.5	37.2
255.vortex	2	81.1	54.3	2	81.1	54.3
256.bzip2	2	158	22.1	2	157	22.2
300.twolf	2	201	34.7	2	200	34.9

Hardware

CPU: Intel Pentium D 3.2GHz
 CPU MHz: 3200
 FPU: Integrated
 CPU(s) enabled: 2 cores, 1 chip, 2 cores/chip
 CPU(s) orderable: 1
 Parallel: No
 Primary Cache: 12k micro-ops I + 16KBD on chip
 Secondary Cache: 1024KB(I+D) on chip
 L3 Cache: N/A
 Other Cache: N/A
 Memory: 4 X 1GB PC2 5300, Unbuffered, Non-ECC
 Disk Subsystem: 1 X 120GB IDE
 Other Hardware: N/A

Software

Operating System: Windows XP Professional SP2
 Compiler: Intel C++ Compiler 8.1 Build 20040802Z
 Microsoft Visual Studio .Net 2003(for libraries)
 SmartHeap Library Version 6.0 from <http://www.microquill.com/>
 File System: NTFS
 System State: Default

Notes/Tuning Information

```
+FDO: PASS1=-Qprof_gen PASS2=-Qprof_use
Base tuning for C programs: -fast +FDO shlW32M.lib
Base tuning for C++ programs: -fast -Qcxx_features +FDO
Portability flags:
176.gcc: -Dalloca=_alloca /F10000000
186.crafty: -DNT_i386
252.eon: Approved stdcpp src.alt used
253.perlbnk: -DSPEC_CPU2000_NTOS -DPERLDLL /MT
254.gap: -DSYS_HAS_CALLOC_PROTO -DSYS_HAS_MALLOC_PROTO
Peak tuning:
164.gzip: -fast -Qansi_alias -Oa +FDO
175.vpr: -fast -Qansi_alias +FDO
176.gcc: basepeak=yes
181.mcf: basepeak=yes
186.crafty: -fast -Qansi_alias -Oa +FDO
197.parser: -fast -Qansi_alias +FDO
252.eon: -fast +FDO
253.perlbnk: -fast -Qansi_alias +FDO shlW32M.lib
254.gap: basepeak=yes
255.vortex: basepeak=yes
```



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Supermicro

PDSLA/E Motherboard(Intel Pentium D 3.2GHz)

SPECint_rate2000 = 31.2

SPECint_rate_base2000 = 31.0

SPEC license #01176 | Tested by: Supermicro | Test date: Jun-2005 | Hardware Avail: May-2005 | Software Avail: Aug-2004

Notes/Tuning Information (Continued)

256.bzip2: -fast -Oa -Qunroll11 +FDO

300.twolf: -fast -O3 +FDO shlw32M.lib

Tested system was built with SC733T-645 chassis and

a 420W (minimum) ATX power supply [4-pin +12V AND (20 or 24-pin)] is required.

See: <http://www.supermicro.com/products/motherboard/DualCore/945/PDSLA.cfm>

The system bus runs at 800 MHz